INSTRUCTIONS



Includes:

- 4 Base Quadrants
- 4 Base Connector Sets (Top and Threaded Bottom)
- 1 Base Stand Set (Top, Bottom, Shaft and Nut)
- 1 Pole Stay Set
- 1 Telescopic Pole
- 8 Large Rings and 5 Small Rings
- Banner



Slot Base Stand Shaft through Bottom Base and connect it to the first Base Quadrant.



Repeat step 1 with the remaining 3 Quadrants. Ensure the Quadrant plugs are on the upper side.



Take the Base Stand Top and slot into the four indents on Base Quadrant.



Secure the Base Stand Shaft onto the base stand thread using Nut



Place a Base Connector Top into the indent on the top of 2 connecting Base Quadrants.



Insert bolt of a Base Connector Set through the top Connector hole so that it appears underneath Base.



Take remaining Base Connector piece and place on bolt under Base. Insert nut into hole and attach to screw.




Tighten the Base Connector bolt on to nut to fasten both Quadrants. Repeat steps 5 to 8 for the remaining Connectors.



Attach the Pole Stay Set to the Base Quadrants, placing each stay through the corresponding hole on the base.




Secure the stays to the base by slotting the locking pin over the stay.



Slide the Telescopic Pole through the hole in the pole stay set.



Attach graphics using the Clips at the top and side. Raise to desired height.





This product is for outdoor promotional use only and should not be left out in extreme weather conditions.

Please use common sense guidelines and do not display this product outdoors when extreme winds or storms may be present.